



# Battery Cabinet Range Summary

## DataSafe<sup>®</sup> HX Batteries and Cabinet Systems

The DataSafe<sup>®</sup> HX range of Valve Regulated Lead Acid (VRLA) batteries has been designed to offer superior solutions for Uninterruptible Power Supply (UPS) markets.

The HX battery cabinet offering now makes the DataSafe HX battery the ideal choice to optimize your UPS system installation, while offering flexibility in allowing customized options enabling you to design the perfect system for your particular application.

DataSafe HX battery cabinet systems are factory pre-wired to minimize installation time. The cabinet design optimizes the overall footprint.

### DataSafe<sup>®</sup> Battery Cabinet Features and Benefits

- ETL, CSA and UL1778 Listed
- Meets International Building Code (IBC) 2012
- Meets California Building Code (CBC) 2013
- Factory pre-wired to reduce installation time
- Flexible design simplifies customization for options including circuit breakers
- Hinged front door and removable rear panels simplify maintenance routines
- Available in beige or black
- Several knockout locations to accommodate specific site wiring needs

## DataSafe<sup>®</sup> XE Batteries and Cabinet Systems

DataSafe XE batteries, manufactured with Thin Plate Pure Lead (TPPL) technology, are specifically designed for shorter duration autonomies. With more power at a shorter duration, DataSafe XE batteries last longer even in higher operating temperature, recharge the battery to better support multiple outages and provides lower energy savings on float.

DataSafe XE batteries are the ideal choice for new hyperscale datacenters where reliability, operating costs and space efficiency are paramount for these demanding applications.

DataSafe XE battery cabinet systems are factory pre-wired to minimize installation time. The cabinet design optimizes the overall footprint.

# DataSafe® Battery Cabinet Systems

## About the DataSafe Battery Cabinet model numbering system

When referring to the model listings below: The first 2 digits represent the available cabinet sizes (all noted as 25 below are also available in 39, 43 or 55). The "E1E" represents EnerSys 1 string (2 strings requires a quote from EnerSys). The following 3 digits indicate the battery type (e.g., 205, 300, etc.). "XD" is representative of the connecting hardware. The following 3 digits represent the Bus voltage (480, 384, etc.). "1B" indicates the breaker, and the following 3 digits indicate the breaker size range (600-030). The "#" indicates the number of auxiliary contacts – choices are 0, 1 or 2. The next digit indicates the inclusion of a Bell Alarm: "0" = no, "1" = yes. The "\*" is the indicator of the breaker option: list "W" for 24 VDC Shunt Trip; "X" for 48 VDC Shunt Trip, "H" for 24 UVR or "J" for 48 UVR. "S1" indicates Seismic IBC 2012. "??" indicates the cabinet color: choose "QB" for beige or "BT" for black. Fuses are no longer offered.

| Model Number              | DataSafe® Battery Type | System Voltage | Number of Strings | Number of Units in Cabinet | Nominal Dimensions |                   |                    | Net Weight lbs (kg) | Package Weight lbs (kg) |
|---------------------------|------------------------|----------------|-------------------|----------------------------|--------------------|-------------------|--------------------|---------------------|-------------------------|
|                           |                        |                |                   |                            | Length inches (mm) | Width inches (mm) | Height inches (mm) |                     |                         |
| 39E1E205XD4801B150#0*S1?? | 12HX205-FR             | 480            | 1                 | 40                         | 36.0 (914)         | 29.5 (749)        | 70.7 (1796)        | 2315 (1050)         | 2345 (1064)             |
| 43E1E300XD4801B200#0*S1?? | 12HX300-FR             | 480            | 1                 | 40                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3005 (1363)         | 3035 (1377)             |
| 55E1E330XD4801B250#0*S1?? | 12HX330-FR             | 480            | 1                 | 40                         | 40.0 (1016)        | 29.5 (749)        | 78.7 (1999)        | 3535 (1603)         | 3565 (1617)             |
| 55E1E400XD4801B250#0*S1?? | 12HX400-FR             | 480            | 1                 | 40                         | 40.0 (1016)        | 29.5 (749)        | 78.7 (1999)        | 3895 (1767)         | 3925 (1780)             |
| 55E1E505XD4801B300#0*S1?? | 12HX505-FR             | 480            | 1                 | 40                         | 40.0 (1016)        | 29.5 (749)        | 78.7 (1999)        | 4815 (21847)        | 4845 (2198)             |
| 55E1E540XD4801B300#0*S1?? | 12HX540-FR             | 480            | 1                 | 40                         | 40.0 (1016)        | 29.5 (749)        | 78.7 (1999)        | 4935 (2238)         | 4965 (2252)             |
| 55E1E560XD4801B300#0*S1?? | 12HX560+FR             | 480            | 1                 | 40                         | 40.0 (1016)        | 29.5 (749)        | 78.7 (1999)        | 4575 (2075)         | 4605 (2089)             |
| 55E1EE76XD4801B250#0*S1?? | 12XE760-FR             | 480            | 1                 | 40                         | 40.0 (1016)        | 29.5 (749)        | 78.7 (1999)        | 3815 (1730)         | 3845 (1744)             |
| 55E1EE10XD4801B300#0*S1?? | 12XE1040-FR            | 480            | 1                 | 40                         | 40.0 (1016)        | 29.5 (749)        | 78.7 (1999)        | 4575 (2075)         | 4605 (2089)             |
| 39E1E205XD3841B150#0*S1?? | 12HX205-FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 70.7 (1796)        | 1971 (894)          | 2001 (908)              |
| 43E1E300XD3841B200#0*S1?? | 12HX300-FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 2525 (1145)         | 2555 (1159)             |
| 43E1E330XD3841B250#0*S1?? | 12HX330-FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 2877 (1305)         | 2907 (1319)             |
| 43E1E400XD3841B250#0*S1?? | 12HX400-FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3165 (1436)         | 3195 (1449)             |
| 43E1E505XD3841B300#0*S1?? | 12HX505-FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3901 (1769)         | 3931 (1783)             |
| 43E1E540XD3841B400#0*S1?? | 12HX540-FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3997 (1813)         | 4027 (1827)             |
| 43E1E560XD3841B400#0*S1?? | 12HX560+FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3709 (1682)         | 3739 (1696)             |
| 43E1EE76XD3841B250#0*S1?? | 12XE760-FR             | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3101 (1407)         | 3131 (1420)             |
| 43E1EE10XD3841B400#0*S1?? | 12XE1040-FR            | 384            | 1                 | 32                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3709 (1682)         | 3739 (1696)             |
| 39E1E205XD3601B150#0*S1?? | 12HX205-FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 70.7 (1796)        | 1885 (855)          | 1915 (869)              |
| 39E1E300XD3601B200#0*S1?? | 12HX300-FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 70.7 (1796)        | 2395 (1086)         | 2425 (1100)             |
| 39E1E330XD3601B250#0*S1?? | 12HX330-FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 70.7 (1796)        | 2725 (1236)         | 2755 (1250)             |
| 43E1E400XD3601B250#0*S1?? | 12HX400-FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3005 (1363)         | 3035 (1377)             |
| 43E1E505XD3601B300#0*S1?? | 12HX505-FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3695 (1676)         | 3725 (1690)             |
| 43E1E540XD3601B400#0*S1?? | 12HX540-FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3785 (1717)         | 3815 (1730)             |
| 43E1E560XD3841B400#0*S1?? | 12HX560+FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3709 (1682)         | 3739 (1696)             |
| 43E1E560XD3601B400#0*S1?? | 12XE760-FR             | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 2945 (1336)         | 2975 (1349)             |
| 43E1EE10XD3601B400#0*S1?? | 12XE1040-FR            | 360            | 1                 | 30                         | 36.0 (914)         | 29.5 (749)        | 78.7 (1999)        | 3515 (1594)         | 3545 (1608)             |

\* HX System Model Numbers are based on 15 minute run time. For less than 15 minutes larger breakers are required.

\*\* XE System Model Numbers are based on 5 minute run time. Custom model numbers available for other system voltages and kW requirements.

| Model Number              | DataSafe®<br>Battery<br>Type | System<br>Voltage | Number<br>of<br>Strings | Number of<br>Units in<br>Cabinet | Nominal Dimensions       |                         |                          | Net<br>Weight<br>lbs<br>(kg) | Package<br>Weight<br>lbs<br>(kg) |
|---------------------------|------------------------------|-------------------|-------------------------|----------------------------------|--------------------------|-------------------------|--------------------------|------------------------------|----------------------------------|
|                           |                              |                   |                         |                                  | Length<br>inches<br>(mm) | Width<br>inches<br>(mm) | Height<br>inches<br>(mm) |                              |                                  |
| 25E1E205XD2401B150#0*S1?? | 12HX205-FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1340<br>(608)                | 1370<br>(621)                    |
| 25E1E300XD2401B200#0*S1?? | 12HX300-FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1680<br>(762)                | 1710<br>(776)                    |
| 25E1E330XD2401B250#0*S1?? | 12HX330-FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1900<br>(862)                | 1930<br>(875)                    |
| 25E1E400XD2401B300#0*S1?? | 12HX400-FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2080<br>(943)                | 2110<br>(957)                    |
| 25E1E505XD2401B400#0*S1?? | 12HX505-FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2540<br>(1152)               | 2570<br>(1166)                   |
| 25E1E540XD2401B400#0*S1?? | 12HX540-FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2600<br>(1179)               | 2630<br>(1193)                   |
| 25E1E560XD2401B400#0*S1?? | 12HX560+FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2420<br>(1098)               | 2450<br>(1111)                   |
| 25E1E760XD2401B300#0*S1?? | 12XE760-FR                   | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2040<br>(925)                | 2070<br>(939)                    |
| 25E1EE10XD2401B400#0*S1?? | 12XE1040-FR                  | 240               | 1                       | 20                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2420<br>(1098)               | 2450<br>(1111)                   |
| 25E1E205XD1921B150#0*S1?? | 12HX205-FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1168<br>(530)                | 1198<br>(543)                    |
| 25E1E300XD1921B200#0*S1?? | 12HX300-FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1440<br>(653)                | 1470<br>(667)                    |
| 25E1E330XD1921B250#0*S1?? | 12HX330-FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1616<br>(733)                | 1646<br>(747)                    |
| 25E1E400XD1921B300#0*S1?? | 12HX400-FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1760<br>(798)                | 1790<br>(812)                    |
| 25E1E505XD1921B400#0*S1?? | 12HX505-FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2128<br>(965)                | 2158<br>(979)                    |
| 25E1E540XD1921B400#0*S1?? | 12HX540-FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2176<br>(987)                | 2206<br>(1001)                   |
| 25E1E560XD1921B400#0*S1?? | 12HX560+FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2032<br>(922)                | 2062<br>(935)                    |
| 25E1E760XD1921B300#0*S1?? | 12XE760-FR                   | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1728<br>(784)                | 1758<br>(797)                    |
| 25E1EE10XD1921B400#0*S1?? | 12XE1040-FR                  | 192               | 1                       | 16                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 2032<br>(922)                | 2062<br>(935)                    |
| 25E1E205XD1441B150#0*S1?? | 12HX205-FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 996<br>(452)                 | 1026<br>(465)                    |
| 25E1E300XD1441B200#0*S1?? | 12HX300-FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1200<br>(544)                | 1230<br>(558)                    |
| 25E1E330XD1441B250#0*S1?? | 12HX330-FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1332<br>(604)                | 1362<br>(618)                    |
| 25E1E400XD1441B300#0*S1?? | 12HX400-FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1440<br>(653)                | 1470<br>(667)                    |
| 25E1E505XD1441B400#0*S1?? | 12HX505-FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1716<br>(778)                | 1746<br>(792)                    |
| 25E1E540XD1441B400#0*S1?? | 12HX540-FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1752<br>(795)                | 1782<br>(808)                    |
| 25E1E560XD1441B400#0*S1?? | 12HX560+FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1644<br>(746)                | 1674<br>(759)                    |
| 25E1E760XD1441B300#0*S1?? | 12XE760-FR                   | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1416<br>(642)                | 1446<br>(656)                    |
| 25E1EE10XD1441B400#0*S1?? | 12XE1040-FR                  | 144               | 1                       | 12                               | 29.0<br>(737)            | 31.5<br>(800)           | 59.0<br>(1499)           | 1644<br>(746)                | 1674<br>(759)                    |

\* HX System Model Numbers are based on 15 minute run time. For less than 15 minutes larger breakers are required.

\*\* XE System Model Numbers are based on 5 minute run time. Custom model numbers available for other system voltages and kW requirements.

# DataSafe® Batteries

## Constant Power Discharge (Battery System kW) to 1.67Vpc at 77°F (25°C)

### 480V System

| Battery Model | End Volts | Minutes |        |        |        |       |       |
|---------------|-----------|---------|--------|--------|--------|-------|-------|
|               |           | 5       | 10     | 15     | 20     | 30    | 60    |
| 12HX205-FR    | 1.67      | 98.88   | 65.76  | 49.44  | 39.36  | 28.56 | 16.08 |
| 12HX300-FR    | 1.67      | 133.92  | 89.52  | 68.16  | 55.44  | 41.76 | 24.48 |
| 12HX330-FR    | 1.67      | 152.88  | 104.40 | 80.64  | 66.24  | 49.44 | 28.80 |
| 12HX400-FR    | 1.67      | 173.28  | 119.52 | 91.44  | 75.15  | 55.68 | 32.64 |
| 12HX505-FR    | 1.67      | 210.48  | 156.72 | 121.44 | 98.88  | 72.24 | 41.52 |
| 12HX540-FR    | 1.67      | 223.44  | 165.84 | 129.60 | 106.56 | 78.24 | 44.64 |
| 12HX560+FR    | 1.67      | 247.68  | 168.48 | 134.40 | 111.60 | 83.76 | 48.96 |
| 12XE760-FR    | 1.67      | 183.36  | 122.64 | 93.60  | 76.80  | 56.88 | 33.12 |
| 12XE1040-FR   | 1.67      | 249.60  | 170.88 | 134.40 | 109.92 | 81.60 | 47.28 |

### 360V System

| Battery Model | End Volts | Minutes |        |        |       |       |       |
|---------------|-----------|---------|--------|--------|-------|-------|-------|
|               |           | 5       | 10     | 15     | 20    | 30    | 60    |
| 12HX205-FR    | 1.67      | 74.16   | 49.32  | 37.08  | 29.52 | 21.42 | 12.06 |
| 12HX300-FR    | 1.67      | 100.44  | 67.14  | 51.12  | 41.58 | 31.32 | 18.36 |
| 12HX330-FR    | 1.67      | 114.66  | 78.30  | 60.48  | 49.68 | 37.08 | 21.60 |
| 12HX400-FR    | 1.67      | 129.96  | 89.64  | 68.58  | 56.34 | 41.76 | 24.48 |
| 12HX505-FR    | 1.67      | 157.86  | 117.54 | 91.08  | 74.16 | 54.18 | 31.14 |
| 12HX540-FR    | 1.67      | 167.58  | 124.38 | 97.20  | 79.92 | 58.68 | 33.48 |
| 12HX560+FR    | 1.67      | 185.76  | 126.36 | 100.80 | 83.70 | 62.82 | 36.72 |
| 12XE760-FR    | 1.67      | 137.52  | 91.98  | 70.20  | 57.60 | 42.66 | 24.84 |
| 12XE1040-FR   | 1.67      | 187.20  | 128.16 | 100.80 | 82.44 | 61.20 | 35.46 |

### 192V System

| Battery Model | End Volts | Minutes |       |       |       |       |       |
|---------------|-----------|---------|-------|-------|-------|-------|-------|
|               |           | 5       | 10    | 15    | 20    | 30    | 60    |
| 12HX205-FR    | 1.67      | 39.55   | 26.30 | 19.78 | 15.74 | 11.42 | 6.43  |
| 12HX300-FR    | 1.67      | 53.57   | 35.81 | 27.26 | 22.18 | 16.70 | 9.79  |
| 12HX330-FR    | 1.67      | 61.15   | 41.76 | 32.26 | 26.50 | 19.78 | 11.52 |
| 12HX400-FR    | 1.67      | 69.31   | 47.81 | 36.58 | 30.05 | 22.27 | 13.06 |
| 12HX505-FR    | 1.67      | 84.19   | 62.69 | 48.58 | 39.55 | 28.90 | 16.61 |
| 12HX540-FR    | 1.67      | 89.38   | 66.34 | 51.84 | 42.62 | 31.30 | 17.86 |
| 12HX560+FR    | 1.67      | 99.07   | 67.39 | 53.76 | 44.64 | 33.50 | 19.58 |
| 12XE760-FR    | 1.67      | 73.34   | 49.06 | 37.44 | 30.72 | 22.75 | 13.25 |
| 12XE1040-FR   | 1.67      | 99.84   | 68.35 | 53.76 | 43.97 | 32.64 | 18.91 |

### 384V System

| Battery Model | End Volts | Minutes |        |        |       |       |       |
|---------------|-----------|---------|--------|--------|-------|-------|-------|
|               |           | 5       | 10     | 15     | 20    | 30    | 60    |
| 12HX205-FR    | 1.67      | 79.10   | 52.61  | 39.55  | 31.49 | 22.85 | 12.86 |
| 12HX300-FR    | 1.67      | 107.14  | 71.62  | 54.53  | 44.35 | 33.41 | 19.58 |
| 12HX330-FR    | 1.67      | 122.30  | 83.52  | 64.51  | 52.99 | 39.55 | 23.04 |
| 12HX400-FR    | 1.67      | 138.62  | 95.62  | 73.15  | 60.10 | 44.54 | 26.11 |
| 12HX505-FR    | 1.67      | 168.38  | 125.38 | 97.15  | 79.10 | 57.79 | 33.22 |
| 12HX540-FR    | 1.67      | 178.75  | 132.67 | 103.68 | 85.25 | 62.59 | 35.71 |
| 12HX560+FR    | 1.67      | 198.14  | 134.78 | 107.52 | 89.28 | 67.01 | 39.17 |
| 12XE760-FR    | 1.67      | 146.69  | 98.11  | 74.88  | 61.44 | 45.50 | 26.50 |
| 12XE1040-FR   | 1.67      | 199.68  | 136.70 | 107.52 | 87.94 | 65.28 | 37.82 |

### 240V System

| Battery Model | End Volts | Minutes |       |       |       |       |       |
|---------------|-----------|---------|-------|-------|-------|-------|-------|
|               |           | 5       | 10    | 15    | 20    | 30    | 60    |
| 12HX205-FR    | 1.67      | 49.44   | 32.88 | 24.72 | 19.68 | 14.28 | 8.04  |
| 12HX300-FR    | 1.67      | 66.96   | 44.76 | 34.08 | 27.72 | 20.88 | 12.24 |
| 12HX330-FR    | 1.67      | 76.44   | 52.20 | 40.32 | 33.12 | 24.72 | 14.40 |
| 12HX400-FR    | 1.67      | 86.64   | 59.76 | 45.72 | 37.56 | 27.84 | 16.32 |
| 12HX505-FR    | 1.67      | 105.24  | 78.36 | 60.72 | 49.44 | 36.12 | 20.76 |
| 12HX540-FR    | 1.67      | 111.72  | 82.92 | 64.80 | 53.28 | 39.12 | 22.32 |
| 12HX560+FR    | 1.67      | 123.84  | 84.24 | 67.20 | 55.80 | 41.88 | 24.48 |
| 12XE760-FR    | 1.67      | 91.68   | 61.32 | 46.80 | 38.40 | 28.44 | 16.56 |
| 12XE1040-FR   | 1.67      | 124.80  | 85.44 | 67.20 | 54.96 | 40.80 | 23.64 |

### 120V System

| Battery Model | End Volts | Minutes |       |       |       |       |       |
|---------------|-----------|---------|-------|-------|-------|-------|-------|
|               |           | 5       | 10    | 15    | 20    | 30    | 60    |
| 12HX205-FR    | 1.67      | 24.72   | 16.44 | 12.36 | 9.84  | 7.14  | 4.02  |
| 12HX300-FR    | 1.67      | 33.48   | 22.38 | 17.04 | 13.86 | 10.44 | 6.12  |
| 12HX330-FR    | 1.67      | 38.22   | 26.10 | 20.16 | 16.56 | 12.36 | 7.20  |
| 12HX400-FR    | 1.67      | 43.32   | 29.88 | 22.86 | 18.78 | 13.92 | 8.16  |
| 12HX505-FR    | 1.67      | 52.62   | 39.18 | 30.36 | 24.72 | 18.06 | 10.38 |
| 12HX540-FR    | 1.67      | 55.86   | 41.46 | 32.40 | 26.64 | 19.56 | 11.16 |
| 12HX560+FR    | 1.67      | 61.92   | 42.12 | 33.6  | 27.90 | 20.94 | 12.24 |
| 12XE760-FR    | 1.67      | 45.84   | 30.66 | 23.40 | 19.20 | 14.22 | 8.28  |
| 12XE1040-FR   | 1.67      | 62.40   | 42.72 | 33.60 | 27.48 | 20.40 | 11.82 |



**EnerSys World Headquarters**  
 2366 Bernville Road  
 Reading, PA 19605, USA  
 Tel: +1-610-208-1991 /  
 +1-800-538-3627

**EnerSys EMEA**  
 EH Europe GmbH  
 Baarerstrasse 18  
 6300 Zug, Switzerland

**EnerSys Asia**  
 152 Beach Road  
 Gateway East Building #11-03  
 Singapore 189721  
 Tel: +65 6508 1780